

ADRES	DEĞER
DATA BELLEĞİ	
0300:0000	21
0300:0001	43
0300:0002	65
0300:0003	87
0300:0004	00
0300:0005	00
0300:0006	00
0300:0007	00
0300:0008	00
0300:0009	00
0300:000A	00
0300:000B	00
0300:000C	00
0300:000D	00
0300:000E	00
0300:000F	00
PROGRAM BELLEĞİ	
0300:0010	B8
0300:0011	00
0300:0012	03
0300:0013	8E
0300:0014	D8
0300:0015	B8
0300:0016	78
0300:0017	56
0300:0018	B9
0300:0019	34
0300:001A	12
0300:001B	BB
0300:001C	00
0300:001D	00
0300:001E	03
0300:001F	07
0300:0020	BB
0300:0021	02
0300:0022	00
0300:0023	13
0300:0024	0F
0300:0025	F4
0300:0026	00
0300:0027	00

MOV AX, 0300 → B8 00 03

MOV DS, AX → 8E D8

MOV AX, 5678 → B8 78 56

MOV CX, 1234 → B9 34 12

MOV BX, 0000 → BB 00 00

ADD AX, [BX] → 03 07

MOV BX, 0002 → BB 02 00

ADC CX, [BX] → 13 0F

HLT → F4

1. SAYI → 8765 4321

2. SAYI → 1234 5678

1.SAYI+2.SAYI → 9999 9999

CX AX